

# TASH Mini Relax



## Specifications

Size (LWD mm):	150 x 90 x 35
Weight (grams):	250
Power:	9V Battery. Auditory prompt when battery is low.
Battery life (reported by manufacturer):	Not reported
User interface:	<input type="checkbox"/> Icons <input checked="" type="checkbox"/> Text – pre-set static function labels. <input checked="" type="checkbox"/> Buttons <input checked="" type="checkbox"/> Lights – small red dot on each button, lit on scan and when button selected. <input checked="" type="checkbox"/> Sound feedback – beep on scan.
Display:	<input checked="" type="checkbox"/> Static <input type="checkbox"/> Dynamic
User control options:	<input type="checkbox"/> Voice <input type="checkbox"/> Touch with finger <input type="checkbox"/> Touch with stylus <input type="checkbox"/> Switch direct <input checked="" type="checkbox"/> Switch scanning – adjustable speed, 1 switch socket + attendant switch. <input type="checkbox"/> Use computer access methods <input type="checkbox"/> Joystick <input type="checkbox"/> Wheelchair joystick
Output types:	<input checked="" type="checkbox"/> Infrared (IR) <input type="checkbox"/> Radio frequency (RF) <input type="checkbox"/> Wi-Fi

	<input type="checkbox"/> Home wiring <input type="checkbox"/> C-Bus or similar <input type="checkbox"/> Relay output <input type="checkbox"/> Macros
Intermediate devices required:	N/A
Number of appliances can control or number of outputs:	Infrared: 6
Backup options:	Nil
Manufacturer:	AbleNet, USA <a href="http://www.ablenetinc.com">www.ablenetinc.com</a>
Distributor:	Communicate AT, Sydney, <a href="http://www.communicateat.com.au">www.communicateat.com.au</a> Spectronics, Brisbane, <a href="http://www.spectronicsinoz.com">www.spectronicsinoz.com</a> Technical Solutions, Melbourne, <a href="http://www.tecsol.com.au">www.tecsol.com.au</a> Zyteq, Melbourne, <a href="http://www.zyteq.com.au">www.zyteq.com.au</a>

## Performance

<b>Lights</b>	
C-Bus light & appliance modules (wireless and wired receiver):	No
Clipsal infrared wall light switch:	Yes
Infrared globe:	Yes
HPM infrared light switch:	Yes
Martec Alpha FourSeasons CFW124CR ceiling light and fan:	Yes
<b>240v appliances</b>	
X10 (via infrared) codes:	Yes
Audio-visual	
Television:	Yes
DVD player:	Yes
Set Top Box:	Yes
Foxtel:	Yes
<b>Phone</b>	
TS phone with infrared controller:	Yes
Possum Sero telephone:	Yes – Using GEWA codes only.
Temperature Control	

Air conditioner via Universal AC Ultra Plus ECU infrared interface:	Yes
<b>Bed</b>	
Bed via Scanning Bed Controller:	Not tested.
<b>General</b>	
Range:	7 m
Ease of programming:	User interface: Attendant can control speed. Training infrared signals: device learnt majority of infrared codes on first attempt. Easy to follow manual for most functions.
Performance reliability:	High