

Hand Wave Dimmer

Model No. WDS01-6A

Hand Wave Dimmer can control DC 12V/24V directly driving led lighting products, such as led cabinet light, led rigid bar and led strip.

- React sensitively within 5inches
- Work as an On/Off switch and dimmer
- Memory function, remember the last scene
- Includes 3M double coated tissue tape for easy placement in any surface
- Ultra low profile and slick design
- Handle big loads up to 144W capability
- 2 years warranty



Specification

Input Voltage	DC 12V/24V
Max Current	6A
Max Power	72W at DC 12V input 144W at DC 24V input
Dimension	1.21*0.34*1.50in
Cable	Input cable 4 5/8 in Output cable 8 1/2 in
Working Temperature	32-165F

Instruction

- 1) Wave your hand in front of switch.
- 2) If stay at the front less than 5 seconds, lights will turn on/off.
- 3) If stay more than 5 seconds, lights will dim up or down.



Wiring Connection

